



## 12W (12V/1A) 1-Phase Power Supply

### Specification:

Input Voltage Range	100VAC to 550VAC;
Input Frequency	50/63Hz;
Inrush Current	<35A Peak@550VAC, Cold Start@25°C;
Input Current	<200mA RMS@100VAC;
Efficiency	>70% typical at full load;
Output Load Voltage	12.0V;
Output Current	1A;
Line and Load Regulation	±5%;
Ripple	<100mV;
Noise	>200mV;
Output overload/Short Circuit Protection	HICCUP;
Over Temperature Protection	Shut down and Resumes to normal operation;
Input Surge Protection	6KV;
Operating Temperature	0°C to 50°C;
Humidity	5% RH to 95% RH;
Indications (Mains on)	Red LED;
Application	CCMS;



**12W (12V/1A) 1-Phase  
Power Supply –Open Type**

**GND Solutions India Pvt. Ltd.**  
[www.gndsolutions.in](http://www.gndsolutions.in)  
Email: [letstalk@gndsolutions.in](mailto:letstalk@gndsolutions.in)